

## REMOVE INTERCOM PAGES FROM SET

Press: Feature \*\*23646

Password: 23646

Press: NEXT to CAPABILITIES

Press: SHOW

Display Shows: DIALING FILTERS

Press: NEXT to SET ABILITIES

Press: SHOW

Display Shows: SHOW SET

Enter in the extension number

Display Shows: SET FILTER 01 or 02

Press: NEXT to PAGING ZONE

Press: CHANGE to NO

Press: RLS to end session